

**Products:**


UNO-2160, UNO-2170, UNO-2171, UNO-2172, UNO-3062, UNO-3062L, UNO-3072,  
UNO-3072L, UNO-3074

**Abstract:**


How to Configure COM3/COM4 in UNO Products

**Description:****Solution:**


1. Select COM3




## 2. Uninstall COM3




## 3. Select COM4 and uninstall it





## 4. Select Add Hardware in Control Panel




## 5. Execute it




**6. Select Add a new hardware device item****7. Select Install the hardware that I manually select from a list (Advanced)**


## 8. Select Ports(COM&LPT) in Common hardware types



## 9. Select Communication Port in standard port types




10. Add it successfully




11. Repeat steps 8~10 to add COM4


12. After that, system will get the com status as below:




13. Select COM3 and click **Set Configuration Manually** in Resources item.




14. Select **Basic configuration 0008** for IRQ and I/O range adjustment




15. Select **I/O Range** and key in 03E8-03EF




16. Select **IRQ** and key in 10




17. Don't restart the computer at this moment



18. Select COM4 and repeat steps 13-16 to set I/O Range: 02E8-02EF / IRQ: 10



19. Restart the computer at this moment



20. Finally, the COM3/COM4 can work well.

