

Advantech AE Technical Share Document

Date	2023/05/26	Release Note Internal External			
Category	□FAQ ∎SOP	Related OS	Win10, Win7		
Abstract	How to set up USDG mode of EKI-1361-CE				
Keyword	USDG mode EKI-1361				
Related					
Product					

Description:

EKI-1361-CE 提供 USGD sever mode 功能。可以讓 EKI-1361 作為 TCP sever,使用者電腦 (TCP Client)可以透過 TCP 協定的 5300 port,連線此 EKI-1361,進而傳送資料。 此架構需先確保使用者電腦 IP,經由內部網路可以 ping 到 EKI-1361 的 IP



Brief Solution - Step by Step:

先針對 EKI-1361 的 WAN 和 LAN IP 設定
 EKI 的 LAN1 IP:192.168.111.231
 EKI 作為 WIFI client 連線到現場網路環境 WIFI AP 拿到
 WAN IP:172.16.13.135
 WAN Gateway: 172.16.13.254



Enabling an Intelligent Planet

AD\ANTECH	EKI-1361-CE WLAN Serial Device Server	Logout		
 millious scialigs 	Information Name	Information Value		
🖉 Port Configuration	Firmware Version	1.05		
🖵 Monitor	Local Hostname			
∆ Alarm	System Time	Fri Mar 10 06:22:20 GMT 2023		
C Administration	System Up Time	0 day 0 hr 45 min 4 sec		
	System Platform	EKI-1361-CE		
	I Memory			
	Information Name Information Value			
	Total Available	63404 kB		
	Free	75960 KB		
	Buffered	5412 kB		
	III. Local Network			
	Information Name	Information Value		
	Local IP Address	192.168.111.231		
	Local Netmask	255.255.255.0		
	MAC Address	74:FE:48:78:50:84		
	Information Name	Information Value		
	WAN IP Address	172.16.13.135		
	WAN Netmask	255.255.255.0		
	WAN Default Gateway	172.16.13.254		
	DNS1	192.168.1.1		
	DNS2	192.168.1.2		

- EKI-1361 設定 USDG server mode
 - 1) Port Configuration>>Port1
 - 2) Mode>>USDG Data mode
 - 3) 其他參數預設即可>>Data Listen Port 5300/Command Listen Port 5400

AD\ANTECH	EKI-1361-CE WLAN Serial Device Server			
Overview	E Home / Port Configuration / Port 1			
One Settings				
🗢 Wireless Settings	Basic Operation Advanced			
🖋 Port Configuration	Port Operation Configuration			
Port 1	Γ	Mode USDG Data Mode 🗸		
🖵 Monitor	Pri	otocol TCP 🗸		
∴ Alarm	Data Idle Time	eutis) 60	(0 - 65535)	
C Administration			(1 - 65535)	
	Data Liste	5300	(1-0000)	
	Command Liste	n Port 5400	(1 - 65535)	
	Response Timeou	ut(ms) 0	(0 - 65535)	
	Frame Brea	ak(ms) 0	(0 - 65535)	
	TCP Mode Extra Options			
	Auto Connect To Peer IP			
	Port Data Buffering			
		Media NONE V		
	When Dr	to Full Stop		
	When Da			
	Pack Conditions (Packet sent immediately when reach 1024 Bytes)			
		ay Size	Bytes (1 - 1024)	



- ◆ 開啟 Port Forwarding 功能
 - 1) Start/End/Local port 5300
 - 2) Local IP:192.168.111.231

ADVANTECH	EKI-1361-CE WLAN Serial Device Server			Log	ogout			
🕮 Overview		E Home / Network Settings / Forwarding / Port Forwarding						
Network Settings								
Wireless WAN	Port Forw Enabled	arding (Only for wireless wan mode)	Start Port	End Port	Local IP	Local Port	Protocol	^ Delete
LAN	3	TEST	5300	5300	192.168.111.231	5300	TCP ¥	Delete
Forwarding	_							
Port Forwarding	Add App	Add Apply						
DMZ								
Security								
🗢 Wireless Settings								

PS:若連線電腦 IP,網路和 EKI-1361 的 WAN IP 不同。
 範例中 TCP client 電腦 IP:192.168.101.101。

請在 EKI-1361 的 LAN Gateway IP 設定為與 WAN Gateway: 172.16.13.254 相同。

AD\ANTECH	EKI-1361-CE WLAN Serial Device Server		
Overview	Home / Network Setting	gs / LAN	
Network Settings			
Wireless WAN	LAN Interface Setup		
LAN	Local Hostname		
Forwarding	Domain Name	lan	
Security	Network Mode	Static IP 🗸	
Wireless Settings			
💅 Port Configuration	IP Address	192.168.1.3	
G Monitor	Subnet Mask	255.255.255.0	
🗘 Alarm	Default Gateway	172.16.13.254	
Administration	DNS	Automatic O Specific	
	Speed & Duplex	Auto-Negotiation 🗸	
	MAC Address	74:FE:48:73:4D:72	



◆ TCP client 電腦使用命令提示字元

1) 輸入:telent 172.16.13.135 5300>>可以順利連線

系統管理員:命令提示字元 Microsoft Windows [版本 10.0.17763.3532] (c) 2018 Microsoft Corporation. 著作權所有,並保留一切權利。 C:\Users\jc>telnet 172.16.13.135_5300					
EKI-1361-CE WLAN Serial Device Server					
Home / Port Configuration / Port 1					
Basic Operation Advanced					
Port Operation Configuration					
Mode	USDG Data Mode				
Protocol	TCP				
Data Idle Timeout(s)	60	(0 - 65535)			
Data Listen Port	5300	(1 - 65535)			
Command Listen Port	5300	(1 - 65535)			
📾 Telnet 172.16.13.133		- 🗆 ×			
TCF Port					

Contact Window and File Link:

https://www.advantech.com/zh-tw/support/details/manual?id=1-293WG6K