

## Advantech AE Technical Share Document

Date	2015 / 03 / 27	SR#	1-2031091314
Category	■ FAQ □ SOP	Related OS	WinCE5
Abstract	Steps of upgrade the new firmware on APAX coupler		
Keyword	Firmware, APAX, update		
Related			
Product	APAX-SU/UAE & BE, APA	4X-5U/1, APAX-5	072

## [Problem]

1. How to upgrade the new firmware on APAX coupler?



## [Solution]

- Download the Advantech APAX/ADAM .Net utility from the website <u>http://support.advantech.com/support/DownloadSRDetail\_New.aspx?SR\_ID=1-2AKUDB</u> <u>&Doc\_Source=Download</u>
- 2. Use Advantech APAX/ADAM .Net utility to search and connect the APAX coupler as APAX-5070. Then set your PC and APAX-5070 at the same network segment.

Advantech Adam/Apax .NET Utility (Wi	in32) Version 2.05.06 (B02)
File Tools Setup Help	
	Information Setting Modbus Address Setting Data Stream Alarm
COM2	
Elemet	AFAX-50/0
10.0.110	Firmware Version 81.21 Download
10.0.0.70-[APAX-5070]	
192.168.229.1	FPGA
	Kemel
Others	Firmware Version A1.30 Download
Favorite Group	Backup System Setting
H- Wireless Sensor Networks	Controller ID 0 🕂 Apply
	Device
	Name APAX-5070
	Description Modbus/TCP Communication Coupler.
	() and ()
	т Арру
	Description Support Modules
	Switch ID
	0
	3 4
	5

- Search the new F/W from website <u>http://support.advantech.com/support/new\_default.aspx</u> Using the keyword as "APAX-5070" to download the new F/W
- 4. Click the "Download" button and confirm and choose the appropriate "CPU" firmware version

Firmware Version	A1.21	Download	
FPGA Firmware Version	A1.05	Download	
Kernel Firmware Version	A1.30	Download	
Backup System Setti Controller ID 0	ng	Apply	
Device			· · · · · · · · · · · · · · · · · · ·



ling an Intelligent Planet
----------------------------

	and the second			
	本機磁碟 (C:) ▶ 使用者 ▶ Neal.Chen ▶ Desk	top		
組合管理 ▼ 新増資料	料夾			
→ 我的要要	名稱	修改日期	類型	大小
	APAX5070A121806UT bin	2014/5/30 下午 04-24	RINI 檔安	147 KB
· · · · · · · · · · · · · · · · · · ·	新道資料本	2014/5/30 十年 10:05	福安密料本	147 10
1 天世	→ 研菇内部文件	2014/7/2下午 03:27	福史咨判太	
1 =0	VIDE	2014/1/8 下午 03-28	檔案容料本	
Pa / # 2# /西		2013/8/9下午 04:08	福塞咨判本	
	TEST 28-05-2014	2014/5/29 上午 05:42	福室咨利本	
X14	120120-00-2014	2027/0/20 2 1 00.12	IN STE ALL IN ALL	
	Information	X	66.43 %	

5. Click the "Download" button and confirm and choose the appropriate "DSP" firmware version

PAX-5070		
Firmware —		
Firmware Version	A1.21	Download
FPGA		
Firmware Version	A1.05	Download
Kemel	r	
Firmware Version	A1.30	Download
	1	



Enabling an Intelligent Planet

📉 開啟茜檔	A REAL PROPERTY AND		-	
	本機磁碟 (C:) ▶ 使用者 ▶ Neal.Chen )	Desktop		
組合管理 ▼ 新増資:	料夾			
☆ 我的最愛	名稱	修改日期	類型	大小
■ 桌面	KernelA130B07UT.ldr	2013/3/18 下午 05:42	LDR 檔案	69 KB
💹 最近的位置	新增資料夾 類型:	LDR 檔案 2014/5/30 上午 10:05	檔案資料夾	
🗼 下載		68.7 KB 2014/7/2 N午 03:27 日期: 2013/3/18	<b>福案資料</b> 夾 堪安 密料本	
		2012/2/0 下午 04-02	<b>田来</b> 具 44 天 虚安 密料 市	
ſ	Downloading			
	, official and a second s			
	Module rebooting			
	,			
			33.79 %	
			55.25 10	
L				
	Information			
	Information		<b>J</b>	
	Information			
	Information			
		aload firmware donel		
	Down	nload firmware done!		
	Down	nload firmware done!		
	Down	nload firmware done!		
	Down	nload firmware done!		
	Down	nload firmware done! 確定		